Issued Date: Jul. 29, 2008
Model No.: V216B1　- L01

Approval

TFT LCD Approval Specification

MODEL NO.: V216B1- L01

Customer:　 _SONY_____

Approved by:_____

Note:

Approved By	TV Head Division
	LY Chen

Reviewed By	QRA Dept.	Product Development Div.
	Tomy Chen	WT Lin

Prepared By	LCD TV Marketing and Product Management Div.	
	WY Li	Steven Tu

1

Version 2.0

CONTENTS

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

REVISION HISTORY

Version	Date	Page (New)	Section	Description
Ver 2.0	Jul. 29,'08	All	All	Approval Specification was first issued. The following describing is the changing history of the spec from preliminary spec. ver.1.1

Version 2.0

Approval

GENERAL SPECIFICATIONS

1.1 OVERVIEW

The V216B1-L01 model is a 21.6 inch wide TFT-LCD module with a 4-CCFL Backlight Unit and a 30-pin 1ch-LVDS interface. This module supports 1366 x 768 (16:9 wide screen) mode and displays up to 16.7 (6-bit+Hi-FRC colors) millions colors. The inverter module for the Backlight Unit is not built in.

1.2 FEATURES

- Excellent Brightness: 400nits

- Contrast Ratio: 800:1

- Fast Response Time: 5ms

- Color Saturation: NTSC 72%

- WXGA (1366 x 768 pixels) Resolution

- DE (Data Enable) Only Mode

- LVDS (Low Voltage Differential Signaling) Interface

- Viewing Angle: 170(H)/160(V) (CR>10) TN Technology

- Color Reproduction (Nature Color)

1.3 GENERAL

Item	Specification	Unit	Note
Active Area	477.417 (H) x 268.416 (V) (21.6" diagonal)	mm	
Bezel Opening Area	481.5 (H) x 272.5 (V)	mm	
Driver Element	a-si TFT active matrix	-	
Pixel Number	1366 x R.G.B. x 768	pixel	
Pixel Pitch (Sub Pixel)	0.1165 (H) x 0.3495 (V)	mm	
Pixel Arrangement	RGB vertical stripe	-	
Display Colors	16.7 millions	color	
Display Operation Mode	Transmissive mode / Normally White	-	
Surface Treatment	Hard coating (3H), AG (Haze 25%)	-	

1.4 MECHANICAL

Item		Min.	Typ.	Max.	Unit	Note
Module Size	Horizontal(H)	500.3	501	501.7	mm	
	Vertical(V)	296.4	297	297.6	mm	
	Depth(D)	16.8	17.3	17.8	mm	To PCB cover
Weight		Na	2350	Na	g	

4

Version 2.0

Approval

2. ABSOLUTE MAXIMUM RATINGS

2.1 ABSOLUTE RATINGS OF ENVIRONMENT

Item	Symbol	Value		Unit	Note
		Min.	Max.		
Storage Temperature	T_{ST}	-20	+60	ºC	(1)
Operating Ambient Temperature	T_{OP}	0	+50	ºC	(1), (2)
Shock (Non-Operating)	S_{NOP}	-	50	G	(3), (5)
Vibration (Non-Operating)	V_{NOP}	-	1.0	G	(4), (5)

Note (1) Temperature and relative humidity range is shown in the figure below.

　　　　(a) 90% RH Max. (Ta $\leqq$ 40 ºC).

　　　　(b) Wet-bulb temperature should be 39 ºC Max. (Ta > 40 ºC).

　　　　(c) No condensation.

Note (2) The maximum operating temperature is based on the test condition that the surface temperature of display area is less than or equal to 65 ºC with LCD module alone in a temperature controlled chamber. Thermal management should be considered in final product design to prevent the surface temperature of display area from being over 65 ºC. The range of operating temperature may degrade in case of improper thermal management in final product design.

Note (3) 11 ms, half-sine wave, 1 time for ± X, ± Y, ± Z.

Note (4) 10 ~ 200 Hz, 10 min, 1 time each X, Y, Z.

Note (5) At testing Vibration and Shock, the fixture in holding the module has to be hard and rigid enough so that the module would not be twisted or bent by the fixture.

Relative Humidity (%RH)

Temperature (ºC)

5

Version 2.0

Approval

2.2 TFT LCD MODULE

Item	Symbol	Value		Unit	Note
		Min.	Max.		
Power Supply Voltage	Vcc	-0.3	6.0	V	
Input Signal Voltage	V_{IN}	-0.3	3.6	V	

2.3 BACKLIGHT UNIT

Item	Symbol	Test Condition	Min.	Type	Max.	Unit	Note
Lamp Voltage	V_W	Ta = 25 ℃	—	—	3000	V_{RMS}	

3. ELECTRICAL CHARACTERISTICS

3.1 TFT LCD MODULE

Ta = 25 ± 2 ºC

Parameter		Symbol	Value			Unit	Note
			Min.	Typ.	Max.		
Power Supply Voltage		V_{CC}	4.5	5.0	5.5	V	(1)
Power Supply Ripple Voltage		V_{RP}	-	-	150	mV	
Rush Current		I_{RUSH}	-	-	3.0	A	(2)
Power Supply Current	White	I_{CC}	-	0.50	-	A	(3)
	Black		-	0.85	0.95	A	
	Vertical Stripe		-	0.75	-	A	
LVDS Interface	Differential Input High Threshold Voltage	V_{LVTH}	+100	-	-	mV	
	Differential Input Low Threshold Voltage	V_{LVTL}	-	-	-100	mV	
	Common Input Voltage	V_{LVC}	1.125	1.25	1.375	V	
	Terminating Resistor	R_T	-	100	-	ohm	
CMOS interface	Input High Threshold Voltage	V_{IH}	2.7	-	3.3	V	
	Input Low Threshold Voltage	V_{IL}	0	-	0.7	V	

Note (1) The module should be always operated within above ranges.

Note (2) Measurement Conditions:

Version 2.0

Vcc rising time is 470us

+5V

0.9Vcc

0.1Vcc

GND

470us

Note (3) The specified power supply current is under the conditions at Vcc = 5 V, Ta = 25 ± 2 ºC, f_v = 60 Hz, whereas a power dissipation check pattern below is displayed.

a. White Pattern

b. Black Pattern

Active Area

Active Area

7

Version 2.0

Approval

c. Vertical Stripe Pattern

Active Area

3.2 CCFL (Cold Cathode Fluorescent Lamp) CHARACTERISTICS (Ta = 25 ± 2 ºC)

Parameter	Symbol	Value			Unit	Note
		Min.	Typ.	Max.		
Lamp Voltage	V_W	-	810	-	V_{RMS}	I_L = 7.0mA
Lamp Current	I_L	6.5	7.0	7.5	mA_{RMS}	
Lamp Turn On Voltage	Vs			1250	V_{RMS}	(2), Ta = 25 ºC
				1450	V_{RMS}	(2), Ta = 0 ºC
Operating Frequency	F_L	40		80	KHz	(3)
Lamp Life Time	L_{BL}	50000			Hrs	(4)

Note (1) The waveform of the voltage output of inverter must be area-symmetric and the design of the inverter must have specifications for the modularized lamp. The performance of the Backlight, such as lifetime or brightness, is greatly influenced by the characteristics of the DC-AC inverter for the lamp. All the parameters of an inverter should be carefully designed to avoid producing too much current leakage from high voltage output of the inverter. When designing or ordering the inverter please make sure that a poor lighting caused by the mismatch of the Backlight and the inverter (miss-lighting, flicker, etc.) never occurs. If the above situation is confirmed, the module should be operated in the same manners when it is installed in your instrument.

Note (2) The lamp starting voltage V_S should be applied to the lamp for more than 1 second after startup. Otherwise the lamp may not be turned on.

Note (3) The lamp frequency may produce interference with horizontal synchronous frequency of the display input signals, and it may result in line flow on the display. In order to avoid interference, the lamp frequency should be detached from the horizontal synchronous frequency and its harmonics as far as possible.

Version 2.0

Approval

Note (4)   The life time of a lamp is defined as when the brightness is larger than 50% of its original value and the effective discharge length is longer than 80% of its original length (Effective discharge length is defined as an area that has equal to or more than 70% brightness compared to the brightness at the center point of lamp.) as the time in which it continues to operate under the condition at Ta = 25 $\pm 2°C$ and I_L = 7.0 mArms.

4. BLOCK DIAGRAM

4.1 TFT LCD MODULE

Note (1) Lamp Connector Part No.:YEONHO 35001HS-02L

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

5. INPUT TERMINAL PIN ASSIGNMENT

5.1 TFT LCD MODULE

Pin No.	Symbol	Description	Note
1	NC	No Connection	(2)
2	NC	No Connection	(2)
3	NC	No Connection	(2)
4	GND	Ground	
5	RX0-	Negative transmission data of pixel 0	
6	RX0+	Positive transmission data of pixel 0	
7	GND	Ground	
8	RX1-	Negative transmission data of pixel 1	
9	RX1+	Positive transmission data of pixel 1	
10	GND	Ground	
11	RX2-	Negative transmission data of pixel 2	
12	RX2+	Positive transmission data of pixel 2	
13	GND	Ground	
14	RXCLK-	Negative of clock	
15	RXCLK+	Positive of clock	
16	GND	Ground	
17	RX3-	Negative transmission data of pixel 3	
18	RX3+	Positive transmission data of pixel 3	
19	GND	Ground	
20	NC	No Connection	(2)
21	SELLVDS	Select LVDS data format	(3) (4)
22	NC	No Connection	(2)
23	GND	Ground	
24	GND	Ground	
25	GND	Ground	
26	VCC	Power supply: +5V	
27	VCC	Power supply: +5V	
28	VCC	Power supply: +5V	
29	VCC	Power supply: +5V	
30	VCC	Power supply: +5V	

Note (1) Connector part no.: P-TWO 196108-30041 (1.0mm FFC)

Note (2) Reserved for CMO internal use, please leave it open

Note (3) Low: JEIDA data format. High/open: VESA data format.

Note (4) The impedance of option pin is 50k ohm.

Note (5) Logic level voltage definition: Low: 0V, High: 3.3V

Version 2.0

Approval

5.2 LVDS DATA MAPPING TABLE

SELLVDS = H or Open   (VESA)

SELLVDS = L (JEIDA)

R0~R7: Pixel R Data (7; MSB, 0; LSB)

G0~G7: Pixel G Data (7; MSB, 0; LSB)

B0~B7: Pixel B Data (7; MSB, 0; LSB)

DE: Data enable signal

Note (1) RSVD (reserved) pins on the transmitter shall be "H" or "L"

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

5.3 BACKLIGHT UNIT

1 HV(Pink)
2 LV(White)

1 HV(Blue)
2 LV(Black)

1 HV(Pink)
2 LV(White)

1 HV(Blue)
2 LV(Black)

Note (1) Lamp Connector Part No.:YEONHO 35001HS-02L

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

5.4 COLOR DATA INPUT ASSIGNMENT

The brightness of each primary color (red, green and blue) is based on the 8-bit gray scale data input for the color. The higher the binary input, the brighter the color. The table below provides the assignment of color versus data input.

Color		Data Signal																							
		Red								Green								Blue							
		R7	R6	R5	R4	R3	R2	R1	R0	G7	G6	G5	G4	G3	G2	G1	G0	B7	B6	B5	B4	B3	B2	B1	B0
Basic Colors	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	Blue	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Cyan	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Magenta	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	White	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
Gray Scale Of Red	Red(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(1)	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(2)	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Red(253)	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(254)	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(255)	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Gray Scale Of Green	Green(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green(1)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0
	Green(2)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Green(253)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0
	Green(254)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0
	Green(255)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
Gray Scale Of Blue	Blue(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Blue(1)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
	Blue(2)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Blue(253)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1
	Blue(254)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0
	Blue(255)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1

Note (1) 0: Low Level Voltage, 1: High Level Voltage

13

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

6. INTERFACE TIMING

6.1 INPUT SIGNAL TIMING SPECIFICATIONS

The input signal timing specifications are shown as the following table and timing diagram.

Signal	Item	Symbol	Min.	Typ.	Max.	Unit	Note
LVDS Receiver Clock	Frequency	1/Tc	60	76	82	MHz	
	Input cycle to cycle Jitter	Trcl	-	-	200	ps	
LVDS Receiver Data	Setup Time	Tlvsu	400	-	-	ps	
	Hold Time	Tlvhd	400	-	-	ps	
Vertical Active Display Term	Frame Rate	Fr	47	50	53	Hz	
			57	60	63		
	Total	Tv	778	806	983	Th	Tv=Tvd+Tvb
	Display	Tvd	768	768	768	Th	-
	Blank	Tvb	10	38	120	Th	-
Horizontal Active Display Term	Total	Th	1442	1560	1936	Tc	Th=Thd+Thb
	Display	Thd	1366	1366	1366	Tc	-
	Blank	Thb	76	194	570	Tc	-

Note (1) Since this module is operated in DE only mode, Hsync and Vsync input signals should be set to
low logic level. Otherwise, this module would operate abnormally.

(2) Please refer to 5.1 for detail information.

INPUT SIGNAL TIMING DIAGRAM

Version 2.0

Approval

LVDS RECEIVER INTERFACE TIMING DIAGRAM

Tc

RXCLK+/-

RXn+/-

Tlvsu

Tlvhd

$$\frac{1T}{14} \qquad \frac{3T}{14} \qquad \frac{5T}{14} \qquad \frac{7T}{14} \qquad \frac{9T}{14} \qquad \frac{11T}{14} \qquad \frac{13T}{14}$$

15

Version 2.0

Approval

6.2 POWER ON/OFF SEQUENCE

To prevent a latch-up or DC operation of LCD module, the power on/off sequence should be as the diagram below.

$0.5 \leqq T_1 \leqq 30ms$
$0 \leqq T_2 \leqq 50ms$
$0 \leqq T_3 \leqq 50ms$
$300ms \leqq T_4$

LVDS Signals

$0 \leqq T_7 \leqq T_2$
$0 \leqq T_8 \leqq T_3$

Option Signals
(SELLVDS)

Backlight (Recommended)
$500ms \leqq T_5$
$100ms \leqq T_6$

Power ON/OFF Sequence

Note (1) The supply voltage of the external system for the module input should follow the definition of Vcc.

Note (2) Apply the lamp voltage within the LCD operation range. When the backlight turns on before the LCD operation or the LCD turns off before the backlight turns off, the display may momentarily become abnormal screen.

Note (3) In case of Vcc is in off level, please keep the level of input signals on the low or high impedance. If T2<0,that maybe cause electrical overstress failure.

Note (4) T4 should be measured after the module has been fully discharged between power off and on period.

Note (5) Interface signal shall not be kept at high impedance when the power is on.

16

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

7. OPTICAL CHARACTERISTICS

7.1 TEST CONDITIONS

Item	Symbol	Value	Unit
Ambient Temperature	Ta	25±2	°C
Ambient Humidity	Ha	50±10	%RH
Supply Voltage	V_{CC}	5.0	V
Input Signal	According to typical value in "3. ELECTRICAL CHARACTERISTICS"		
Inverter Current	I_L	7.0	mA
Inverter Driving Frequency	F_L	50	KHz
Inverter	Ampower (27-D024817)		

7.2 OPTICAL CHARACTERISTICS

Item		Symbol	Condition	Min.	Typ.	Max.	Unit	Note
Contrast Ratio		CR		600	800		-	(2)
Response Time		T_R			1.3	2.2	ms	(3)
		T_F			3.7	5.8		
Center Luminance of White		L_C		300	400			(4)
White Variation		δW				1.3	-	(7)
Cross Talk		CT				4	%	(5)
Color Chromaticity	Red	Rx	θ_x=0°, θ_Y =0° Viewing Angle at Normal Direction	Typ. -0.03	0.644	Typ. +0.03	-	(6)
		Ry			0.331		-	
	Green	Gx			0.273		-	
		Gy			0.588		-	
	Blue	Bx			0.151		-	
		By			0.061		-	
	White	Wx			0.285		-	
		Wy			0.293		-	
	Color Gamut	CG		68	72		%	NTSC Ratio
Viewing Angle	Horizontal	θ_x+	CR≥10	75	85		Deg.	(1)
		θ_x-		75	85			
	Vertical	θ_Y+		70	80			
		θ_Y-		70	80			

Note (1)　Definition of Viewing Angle (θx, θy):

　　　　　Viewing angles are measured by EZ-Contrast 160R (Eldim)

17

Version 2.0

Approval

Normal

$\theta x = \theta y = 0^\circ$

$\theta y-$ $\theta y+$

$\theta X- = 90^\circ$ x-

12 o'clock direction

$\theta y+ = 90^\circ$

$\theta x-$

y+

$\theta x+$

6 o'clock

y-

$\theta y- = 90^\circ$

x+ $\theta X+ = 90^\circ$

Note (2) Definition of Contrast Ratio (CR):

The contrast ratio can be calculated by the following expression.

Contrast Ratio (CR) = L255 / L0

L255: Luminance of gray level 255

L 0: Luminance of gray level 0

CR = CR (5),

CR (X) is corresponding to the Contrast Ratio of the point X at the figure in Note (7).

Note (3) Definition of Response Time (T_R, T_F):

Gray Level 255   Gray Level 255

100%
90%

Optical

Response

Gray Level 0

10%
0%

T_R T_F Time

Note (4) Definition of Luminance of White (L_C):

Measure the luminance of gray level 255 at center point and 5 points

$L_C = L (5)$

L (X) is corresponding to the luminance of the point X at the figure in Note (7).

Note (5) Definition of Cross Talk (CT):

18

Version 2.0

Approval

$CT = | Y_B - Y_A | / Y_A \times 100 \ (\%)$

Where:

Y_A = Luminance of measured location without gray level 0 pattern (cd/m^2)

Y_B = Luminance of measured location with gray level 0 pattern (cd/m^2)

Active Area

(0, 0)

$Y_{A, U}$ (D/2,W/8)

$Y_{A, L}$ (D/8,W/2)

Gray 128

$Y_{A, R}$ (7D/8,W/2)

$Y_{A, D}$ (D/2,7W/8)

(D,W)

Active Area

(0, 0)

$Y_{B, U}$ (D/2,W/8)

(D/4,W/4)

$Y_{B, L}$ (D/8,W/2)

Gray 0

$Y_{B, R}$ (7D/8,W/2)

(3D/4,3W/4)

$Y_{B, D}$ (D/2,7W/8)

Gray 128

(D,W)

Note (6) Measurement Setup:

The LCD module should be stabilized at given temperature for 1 hour to avoid abrupt temperature change during measuring. In order to stabilize the luminance, the measurement should be executed after lighting Backlight for 1 hour in a windless room.

LCD Module

LCD Panel

Center of the Screen

Display Color Analyzer

(Minolta CA210)

Light Shield Room

(Ambient Luminance < 2 lux)

Note (7) Definition of White Variation (δW):

Measure the luminance of gray level 255 at 5 points

δW = Maximum [L (1), L (2), L (3), L (4), L (5)] / Minimum [L (1), L (2), L (3), L (4), L (5)]

19

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

Horizontal Line

Active Area

8. DEFINITION OF LABELS

20

**Version 2.0**

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

8.1 CMO MODULE LABEL

The barcode nameplate is pasted on each module as illustration, and its definitions are as following explanation.

(a)   Model Name: V216B1-L01

(b)   Revision: Rev. XX, for example: A0, A1… B1, B2… or C1, C2…etc.

(c)   Serial ID: X X X X X X X Y M D L N N N N

- Serial No.
- Product Line
- Year, Month, Date
- CMO Internal Use
- CMO Internal Use
- Revision
- CMO Internal Use

(d) Production Location:XXXX, for example:TAIWAN or CHINA .

Serial ID includes the information as below:

(a) Manufactured Date: Year: 0~9, for 2000~2009

Month: 1~9, A~C, for Jan. ~ Dec.

Day: 1~9, A~Y, for 1^{st} to 31^{st}, exclude I ,O, and U.

(b) Revision Code: Cover all the change

(c) Serial No.: Manufacturing sequence of product

(d) Product Line: 1 -> Line1, 2 -> Line 2, …etc.

9. PACKAGING

21

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

9.1 PACKING SPECIFICATIONS

(1)   10 LCD TV modules / 1 Box

(2)   Box dimensions: 563(L) X 408 (W) X 530 (H)

(3)   Weight: approximately 25Kg (10 modules per box)

9.2 PACKING METHOD

Figures 9-1 and 9-2 are the packing method

Figure.9-1 Packing Method

22

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

**Sea / Land Transportation**
(40ft HQ Container)
Pallet Stack: L840*W1150*H2530mm
Gross:630kg

Sea / Land Transportation
(40ft HQ Container)
Pallet Stack: L840*W1150*H2155mm
Gross:530kg

Air Transportation

Pallet Stack:L840*W1150*H1265m
Gross:315kg

Figure.9-2 Packing Method

23

Version 2.0

Approval

10. PRECAUTIONS

10.1 ASSEMBLY AND HANDLING PRECAUTIONS

(1) Do not apply rough force such as bending or twisting to the module during assembly.

(2) It is recommended to assemble or to install a module into the user's system in clean working areas. The dust and oil may cause electrical short or worsen the polarizer.

(3) Do not apply pressure or impulse to the module to prevent the damage of LCD panel and backlight.

(4) Always follow the correct power-on sequence when the LCD module is turned on. This can prevent the damage and latch-up of the CMOS LSI chips.

(5) Do not plug in or pull out the I/F connector while the module is in operation.

(6) Do not disassemble the module.

(7) Use a soft dry cloth without chemicals for cleaning, because the surface of polarizer is very soft and easily scratched.

(8) Moisture can easily penetrate into LCD module and may cause the damage during operation.

(9) High temperature or humidity may deteriorate the performance of LCD module. Please store LCD modules in the specified storage conditions.

(10) When ambient temperature is lower than 10ºC, the display quality might be reduced. For example, the response time will become slow, and the starting voltage of CCFL will be higher than that of room temperature.

10.2 SAFETY PRECAUTIONS

(1) The startup voltage of a backlight is over 1000 Volts. It may cause an electrical shock while assembling with the inverter. Do not disassemble the module or insert anything into the backlight unit.

(2) If the liquid crystal material leaks from the panel, it should be kept away from the eyes or mouth. In case of contact with hands, skin or clothes, it has to be washed away thoroughly with soap.

(3) After the module's end of life, it is not harmful in case of normal operation and storage.

10.3 SAFETY STANDARDS

The LCD module should be certified with safety regulations as follows:

(1) UL60950-1 or updated standard.

(2) IEC60950-1 or updated standard.

(3) UL60065 or updated standard.

(4) IEC60065 or updated standard.

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

11. MECHANICAL CHARACTERISTIC

Version 2.0

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

MODULE_X

104.7
(110)
(90.35)
(80)

P-TWO: 196108-30041
or EQUIVALENT

(235)

(150)

MODULE_Y

60

PIN 1

40

(235)

150 ±15 (LAMP POWER WIRE LENGTH)

150 ±15 (LAMP POWER WIRE LENGTH)

CONNECTOR: YEONHO 35001HS-02L
CONNECTOR 1: PIN1-PINK (HV)
　　　　　　　PIN2-WHITE(LV)
CONNECTOR 2: PIN1-BLUE (HV)
　　　　　　　PIN2-BLACK(LV)

CONNECTOR: YEONHO 35001HS-02L
CONNECTOR 1: PIN1-PINK (HV)
　　　　　　　PIN2-WHITE(LV)
CONNECTOR 2: PIN1-BLUE (HV)
　　　　　　　PIN2-BLACK(LV)

CHI MEI
OPTOELECTRONICS CORP.
奇美電子股份有限公司

APPROVED:	Davis Wang	DWG NO.:	V2162410IA
CHECKED:	Steven Lin	DATE:	2008/05/20
DESIGNER:	Catking Yang	PART NO.:	
DRAWER:	Catking Yang	REV.:	A
TITLE:	OUTLINE_V216B1-L01	UNIT:	MM	SCALE: 1:1	SHEET: 2/3

"CHI MEI" COPYRIGHT 2001, ALL RIGHTS RESERVED, COPYING FORBIDDEN.

First Release

MARK	DESCRIPTION	DATE	CHANGE BY	APPROVAL BY	ECN NO.
		2008/05/20 Catking Yang			

26

Issued Date: Jul. 29, 2008
Model No.: V216B1 - L01

Approval

NOTE:
1.IT IS RECOMMENDED THAT ALL SCREWS SHOULD BE INCLUDED
  WHEN CMO'S PRODUCT IS APPLIED IN ORDER TO GUARANTEE STRUCTURE STRENGTH OF PRODUCT.
2.SCREW: M3 (PITCH 0.5 / MACHINE)
3.MAX. TORQUE: 4 KGF-CM.

CHI MEI
OPTOELECTRONICS CORP.   奇美電子股份有限公司

DWG NO:	V21624101A	UNIT: MM
DATE:	2008/05/20	SCALE: 1:1
PART NO.:		SHEET: 3/3
REV.:	A	

APPROVED: Davis Wong
CHECKED: Steven Lin
DESIGNER: Catking Yang
DRAWER: Catking Yang
TITLE: OUTLINE_V216B1-L01

"CHI MEI" COPYRIGHT 2001, ALL RIGHTS RESERVED, COPYING FORBIDDEN.

First Release   2008/05/20 Catking Yang
MARK DESCRIPTION   DATE   CHANGE BY   APPROVAL BY   ECN NO.

27

Version 2.0